

Installation Guide

DFT 200





Dedicated Micros UK Ltd.

11, Oak Street, Swinton, Pendlebury.
Manchester.
M27 4FL.
United Kingdom.

Direct Telephone: 0161 727 3241 Direct Fax: 0161 794 4464
Outside UK. Telephone: Int +(44) 161 727 3241 Fax: Int +(44) 161 794 4464

Dedicated Micros U.S.A. Inc.

11515 Sunset Hills Road, Reston, Virginia 22090, U.S.A.
Telephone: Int +(703) 904 7738 Fax: Int +(703) 904 7743

Dedicated Micros (Australia) PTY.

Unit 1, 30 Leighton Place, Hornsby NSW2077, Australia.
Telephone: Int +(612) 482 1857 Fax: Int +(612) 482 1657

Dedicated Micros (Asia) Ltd.

1 Tannery Road, #05-04/05 Cencon 1, Singapore 1334.
Telephone: Int +(65) 741 0138 Fax: Int +(65) 741 0221

Dedicated Micros (Belgium) Ltd.

Interleuvenlaan 64, B-3001 Leuven, Belgium.
Telephone: Int +(32) 16 40 12 28 Fax: Int +(32) 16 40 02 43

© **Dedicated Microcomputers Ltd. 1995**

All rights reserved. No part of this publication may
be reproduced or distributed in any form or by any
means without the prior written permission of the
publisher.

Microcom ® is a registered trademark of:
Microcom Systems, Inc.

Gandalf ® is a registered trade mark of:
Gandalf Digital Communications Ltd.

Safety

Read Instructions - All the safety and operating instructions should be read before the unit is operated.

Retain instructions - The safety and operating instructions should be retained for future reference.

Heed warnings - All warnings on the unit and in the operating instructions should be adhered to.

Follow instructions - All operating and user instructions should be followed.

Cleaning - Unplug the unit from the outlet before cleaning. Do not use liquid cleaners or aerosol cleaners. Use a damp cloth for cleaning.

Attachments - Do not use attachments not recommended by the product manufacturer as they may cause hazards.

Water and Moisture - Do not use this unit near water - for example, near a bath tub, wash bowl, kitchen sink, or laundry tub, in a wet basement, near a swimming pool, in an unprotected outdoor installation, or any area which is classified as a wet location.

Accessories - Do not place this unit on an unstable stand, tripod, bracket, or mount. The unit may fall, causing serious injury to a person and serious damage to the unit. Use only with a stand, tripod, bracket or mount recommended by the manufacturer, or sold with the product. Any mounting of the unit should follow the manufacturer's instructions, and should use a mounting accessory recommended by the manufacturer.



An appliance and cart combination should be moved with care. Quick stops, excessive force, and uneven surfaces may cause the appliance and cart combination to overturn.

Ventilation - Openings in the enclosure are provided for ventilation and to ensure reliable operation of the unit and to protect it from overheating. These openings must not be blocked or covered. This unit should not be placed in a built-in installation unless proper ventilation is provided.

Power Sources - This unit should be operated only from the type of power source indicated on the manufacturer's label. If you are not sure of the type of the power supply you plan to use consult your appliance dealer or local power company. For units intended to operate from battery power, or other sources, refer to operating instructions.

Grounding or Polarization - This unit may be equipped with a polarized alternating-current line plug (a plug having one blade wider than the other). This plug will fit into the power outlet only one way. This is a safety feature. If you are unable to insert the plug fully into the outlet, try reversing the plug. If the plug should still fail to fit, contact your electrician to replace your obsolete outlet. Do not defeat the safety purpose of the polarized plug.

Alternately this unit may be equipped with a 3-wire grounding-type plug, a plug having a third (grounding) pin. This plug will only fit into a grounding-type power outlet. This is a safety feature. If you are unable to insert the plug into the outlet, contact your electrician to replace your obsolete outlet. Do not defeat the safety purpose of the grounding-type plug.

Power-Cord Protection - Power-supply cords should be routed so that they are not likely to be walked on or pinched by items placed upon or against them, paying particular attention to cords at plugs, convenience receptacles, and the point where they exit from the appliance.

Overloading - Do not overload outlets and extension cords as this can result in a fire or electric shock.

Object and Liquid Entry - Never push objects of any kind into this unit through openings as they may touch dangerous voltage points or short-out parts that could result in a fire or electric shock. Never spill liquid of any kind on the unit.

Servicing - Do not attempt to service this unit yourself as opening or removing covers may expose you to dangerous voltage of other hazards. Refer all servicing to qualified service personnel.

Damage Requiring Service - Unplug the unit from the outlet and refer servicing to qualified service personnel under the following conditions:

(a) When the power-supply cord or plug is damaged.

(b) If liquid has been spilled, or objects have fallen into the unit.

(c) If the unit has been exposed to rain or water.

(d) If the unit does not operate normally by following the operating instructions.

Adjust only those controls that are covered by the operating instructions as an improper adjustment of other controls may result in damage and will often require extensive work by a qualified technician to restore the unit to its normal operation.

(e) If the unit has been dropped or the cabinet has been damaged.

(f) When the unit exhibits a distinct change in performance this indicates a need for service.

Replacement Parts - When replacement parts are required, be sure the service technician has used replacement parts specified by the manufacturer. A replacement lithium battery is available from Dedicated Micros Ltd.

Safety Check - Upon completion of any service or repairs to this unit, ask the service technician to perform safety checks to determine that the unit is in proper operating condition.

Coax Grounding - If an outside cable system is connected to the unit, be sure the cable system is grounded.

UNPACKING - The shipping carton is the safest container in which the unit may be transported. Save it for possible future use.

WARNING - TO PREVENT FIRE OR SHOCK HAZARD, DO NOT EXPOSE THIS EQUIPMENT TO RAIN OR MOISTURE.



The lightning flash with arrowhead symbol within an equilateral triangle is intended to alert the user of this equipment that there are dangerous voltages within the enclosure which may be of sufficient magnitude to constitute a risk of electric shock.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

FCC AND DOC INFORMATION

(U.S.A. and Canadian Models Only)

WARNING

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

If necessary, the user should consult the dealer or an experienced radio/television technician for corrective action. The user may find the following booklet prepared by the Federal Communications Commission helpful: "How to identify and Resolve Radio-TV Interference Problems". This booklet is available from the U.S. Government Printing Office, Washington, DC20402, Stock No. 004-000-00345-4.

This reminder is provided to call the CATV system installer's attention to Art. 820-40 of the NEC that provides guidelines for proper grounding and, in particular, specifies that the cable ground shall be connected to the grounding system of the building, as close to the point of cable entry as practical.

Table of Contents

1	Introduction	1
	DFT-0200 Receiver	
	Telemetry	
	Audio option	
2	Unpacking the unit	3
	2.1 Items in packing	3
	2.2 Packing the DVST	3
3	Operation	5
	3.1 Keyboard <i>Fig: 1 Keyboard</i>	5
	3.2 Making a call	6
	3.3 Disconnecting a call	6
	3.4 Viewing a remote system	7
	FULL Screen	
	QUAD Split	
	MULTI screen	
	PERISCOPE shot	
	Select High / Low resolution.	
	Select Colour / Monochrome	
	Freeze full screen image	
	3.5 Controlling telemetry cameras	9
	3.6 Callback	9
	3.7 Alarm indication on baseline	10
	3.8 Freeze all alarms	10
	3.9 Offline frozen alarm	10
	3.10 Dialog box	10
	3.11 Built in image storage	11
	3.12 Remote Control (Optional)	11
4	Installation	15
	4.1 Rear Panel connections	15
	<i>Fig: 2 Rear panel layout</i>	
	<i>Key to Fig: 2</i>	
	4.2 Power Inputs	15
	4.3 Monitor Outputs	16
	<i>Fig: 3 Monitor connections</i>	

4.4	Setting up the Monitor	16
4.5	Video Recorder Connection	17
	<i>Fig: 4 Alarm input/output connections</i>	
5	Setup (Basic)	19
5.1	General	19
5.2	Set up via keyboard	19
	<i>Fig: 5 PC Connections</i>	
5.3	Remote Setup	21
5.4	DVST Commands	21
	HELP	
	QUIT	
	RESET	
	VIEW	
5.5	Define Camera Inputs	22
	MAX=nn	
	COL=nn	
	MON=nn	
	CAMnn=	
	AUX=	
5.6	Define Auxiliary Ports, 1, 2, 3	23
	PORT=	
6	P.C. Operation	25
6.1	Set up via PC	25
6.2	PC and Printer Connection	25
7	Demonstration Mode	27
7.1	Demonstration mode	27
	DEMO=	
	EXTCLK=	
7.2	Demo Cable	28
	<i>Fig: 6 Wiring details for demo cable</i>	
7.3	Connecting the demo cable	29
	Single cable operation	
	Dual cable operation	
	<i>Fig: 7 Demo Cable Connections</i>	
	<i>Fig: 8 Demo cable connections - dual mode</i>	

8	Modems	31
8.1	PSTN Connection (Modem)	31
8.2	MODEM Commands	31
	MODEM=	
	MODEM	
	MBAUD=	
	MODEM2=	
	PORT=	
8.3	Modem configuration strings	33
	MODSTR=	
	MOD2STR=	
	USER=...	
	SEND	
	DIAL=	
8.4	Modem Operation	35
8.5	Connecting a modem in direct mode	36
	Call request	
	Call answer request	
	Call disconnect.	
	Configuration of modem in direct mode	
8.6	Using a modem in ATMODE	37
	Call request	
	Call answer request	
	Call disconnect	
8.7	General settings for modems in ATMODE	37
	MODEM Requirements	
	All modems	
	Synchronous Modems:	
	Asynchronous Modems:	
8.8	MOTOROLA VFAST	39
	Country Specific Settings	
	No Dialtone	
	Transmission speed	
8.9	Microcom V3242	41
	Synchronous mode :	
	DIP Switch Settings Synchronous Operation	
	DIP Switch Settings Asynchronous Operation	
8.10	Trailblazer	42
	Async mode	
8.11	OCTOCOM OSI 8196A	43

9	Terminal Adapters	45
9.1	ISDN Connection (Terminal Adapter)	45
	DUALISDN=	
	ISDN=	
9.2	Connecting a terminal adapter in direct mode	46
	Making a Call	
	Answering a Call	
	Call disconnection	
	Configuring a Terminal Adapter for direct mode operation	
9.3	Gandalf TA1	47
	Direct Connection	
9.4	ASCOM 5000 / CITAM	48
	ATMODE	
	<i>Fig 9: ASCOM internal dip switch settings (ATMODE)</i>	
	X21	
	<i>Fig 10: ASCOM internal dip switch settings (X21)</i>	
9.5	Dataflex TA	52
	SEND CONFIGURATION STRING	
10	Calls	53
10.1	Passwords	53
	PASSWORD=	
	PASSn=	
	SPASSWORD=	
10.2	On Screen Titling	54
	SYSTEM=	
	TIME=	
	DATE=	
	TLPOS=	
	TDPOS=	
10.3	Telephone Number Entries / Connection Commands	55
	TELn=	
	TELn	
	TYPEn=	
	TIMER=	
	DIALCLR=	
10.4	Callback	56
	CALLBACK=	
	MYMODEM=	
	MYISDN0=	
11	Images and Transmission	59
	Screen display - Periscope mode	
11.1	Image size	60
	Target image size =	

12 Alarms & Events	61
12.1 ALARM Settings	61
ASYS=	
AON=n	
AOFF=n	
ANOnn	
ANCnn	
Images transmitted on alarm	
ATYPEn=	
AOUT=	
ALMODE=	
ADIAL=n	
13 Audio	65
13.1 Equipment Required but not Supplied	65
<i>Fig: 11 End Panel Layouts</i>	
13.2 Connectint the DAL100	66
Microphone	
Speaker	
Power Supply	
DVST Connections	
<i>Fig: 12 Microphone Connection</i>	
14 Cable Assemblies	67
14.1 X21 to V35 Cable Assembly	68
14.2 X21 Cable Assembly	69
14.3 V24 ASYNC Cable Assembly	70
14.4 V24 SYNC Cable Assembly	71
14.5 RS232 Cable Assembly (DVST-PC)	72
14.6 RS232 Cable Assembly (DVST-DAL)	73
15 Glossary	75
16 Returns Procedure	77

1 Introduction

DVST is the generic name for a range of products designed to store and transmit digital pictures at a higher quality and speed than previously possible.

DFT-0200 Receiver

The receiver will process the image received over ISDN or PSTN telephone lines. The images are stored on the internal disk drive.

Telemetry

The DFT 0200 can control telemetry cameras at a remote site using Dedicated Micros telemetry equipment.

Audio option

Audio transmission is available allowing two way, half duplex, (one way at a time) communication. (Transmission medium must be 19200 baud or faster)

This page is intentionally blank

2 Unpacking the unit

2.1 Items in packing

The unit should be carefully unpacked and the packing materials retained. Check that all the contents on the following checklist are present:

- DVST Unit
- Power Lead with molded IEC connector
- Rack mount conversion kit
- Installation Guide
- Returns procedure(single sheet)
- Customer returns note(single sheet)

The keyboard is packed separately.

- Keyboard with integral 2m lead

2.2 Packing the DVST

If the DVST is to be returned for repair or transported to another location the original packing should be used.

The rack mount kit, if fitted, should be removed before transit.

The unit should first be wrapped in the polythene bag. The preformed end pieces are then placed at either side of the unit which can then be placed inside the cardboard box. The box should be firmly sealed using appropriate tape.

If the unit is to be returned for repair ensure a valid returns note is clearly written on the side of the box.

3 Operation

3.1 Keyboard




Fig: 1 Keyboard

- 1 Full 'Press to select full screen display.
- 2 QuadUse to select 4 section (Quad) screen.
- 3 Multi-screenPress to select 16 camera display or Periscope mode display (dependent on status of Hi/Lo key).
- 4 Setup Enter setup mode.
- 5 Telem Selects telemetry control of PTZ (fully functional) cameras.
- 6 CoLA toggle action key to request Colour or Monochrome transmission of images.
- 7 Hi/Lo ResRequests High or Low resolution transmission of images.
- 8 LinePress the Line key to display the Dial list of pre-programmed telephone numbers (Dial Menu). Use UP/DOWN arrow keys to select telephone number, press line key again to dial selected number. Press and retain line key to disconnect.
- 9 RestartPress to remove the dial menu from the screen.
- 10 Seq Sequence Key - not yet implemented.
- 11 Arrow/ numeric Directional control for telemetry, numeric entry in setup mode, segment control in quad and multi-screen modes, select telephone number, request callback.
- 12 Zoom / Preset Selects x2 zoom, if Telemetry is selected requests a preset position when followed by a numeric key.
- 13 Function keys Use dependent on telemetry and alarm options fitted.
- 14 Hold Not implemented
- 15 Camera SelectPress to view selected camera in full screen mode or select the camera to be viewed in each segment of a quad or multi screen. Acknowledge incoming alarms.

3.2 Making a call

Press the LINE key.

The dial menu will appear on the screen.

Select the desired number by using the UP/DOWN arrow keys. (2/8)

Press the LINE key when the desired number is highlighted.

The dial menu will be replaced by the dialog box which will indicate how the call is progressing.

When connected the system name of the remote site will appear on the bottom of the screen and then pictures from the remote site will be received.

Note: When the dial menu is on the screen NO INCOMING CALLS ARE ALLOWED, the dial menu screen can be cleared at any time by pressing the RESTART key.

The dial menu will automatically clear from the screen after a user defined period of time.

3.3 Disconnecting a call

Pressing the LINE key at any time will disconnect the call and the dialog box will report on the length of call along with remote system details.

3.4 Viewing a remote system

There are several different display options available. These can be high or low resolution, colour or monochrome.

FULL Screen

The FULL key selects a full screen display.

Press the zoom key, (number 5 on the numeric keypad) to view a section of the image using x2 electronic zoom. The magnified area is moved around by using the directional arrow keys. On screen indication "ZOOMED" appears in the top left corner of the screen when the Zoom feature is in use. Press full or zoom to restore normal size image.

The Hi/Lo key toggles resolution, The Col key toggles between Colour and Monochrome operation.

QUAD Split

The QUAD key selects a 4 section screen. This is initially cameras 1,2,3 & 4 although any camera can be selected to be displayed in any position.

The arrow keys are used to take control of individual screen segments, the segment in use will show a ">" to the left of the camera number. Press any camera key to display the corresponding camera in that segment. A "*" will show to left of camera number to indicate the camera has been accessed.

The Hi/Lo and Col keys have the same operation as in the Full screen mode.

MULTI screen

When the MULTI screen key is pressed the current status of the Hi/Lo key is critical. If Hi is selected (lamp is lit) a sixteen way display appears on screen. If Lo is selected the PERISCOPE shot display is actuated.

PERISCOPE shot

PERISCOPE shot display is a unique high speed display updating just a specific section of the screen containing the full image.

This is selected by pressing the MULTI screen key and ensuring the Hi/Lo key status is low (lamp off).

The Col key works as normal.

Select High / Low resolution.

Resolution is selected by a toggle action key marked Hi/Lo. High resolution is indicated by the key lamp being illuminated.

As indicated above the Hi/Lo key has a different operation in MULTI screen and PERISCOPE shot displays.

Note: Update times will be faster using Low resolution.

Select Colour / Monochrome

The Col key selects transmission of images in either colour or monochrome.

Note: Monochrome (black & white) images are transmitted 20% faster than colour images.

Freeze full screen image

An alarm image is displayed as frozen full screen image. While the image is frozen the HOLD key lamp is illuminated.

3.5 Controlling telemetry cameras

Control of a remote system's cameras is possible using DM DTMF equipment.

Select the required camera to be displayed FULL screen or periscope.

Press the TELEM key on the extended keyboard, when the TELEM lamp is lit, all the keyboard telemetry functions are available to the operator.

When the directional arrow keys or the ZOOM + or ZOOM - keys are in use the centre section of the screen (about one quarter screen size) drops to low resolution and is updated rapidly to allow the operator to accurately position the telemetry controlled camera.

When the FOCUS +or FOCUS - keys are used the centre section of the screen (about one sixteenth size) is displayed in very high resolution along with a fast update speed. This allows the operator to accurately focus the telemetry camera.

3.6 Callback

The callback feature allows an operator at a monitoring station to call a DFT0100, DFT015 or DFT0200 transmitter on site and configure the unit to automatically call them back, ensuring that the telephone call is charged to the transmitting and not the receiving site.

On sending a callback request, the monitoring station disconnects and waits for the transmitting site to call back. With callback enabled, connection time is approximately twice that of normal connection time.

3.7 Alarm indication on baseline

When a system is receiving alarms the baseline on the display alternates between the remote system ID and an alarm banner line.

The banner line indicates which alarms are presently active at the remote site. These appear as numbers 1 to 16, placed in numeric order. When an alarm input is not active the number appears as a dot, or pair of dots.

3.8 Freeze all alarms

Each alarm activation stores the corresponding camera image and transmits the frozen image to the receiver.

The frozen pictures with a record of the time, date and camera number will be stored in memory until the alarms have been acknowledged.

Alarms are acknowledged by pressing the corresponding camera key that is displayed on the screen. If another alarm is pending, that frozen on alarm image will be displayed and must be cleared in a similar way.

When all alarms have been acknowledged the alarm banner line will no longer alternate with the system ID and control of the remote site can continue as normal.

3.9 Offline frozen alarm

Each offline alarm activation stores the corresponding camera image and transmits the frozen image to the receiver.

Each frozen alarm is acknowledged by pressing the corresponding camera key that is displayed on the screen.

Any further alarms on the system do not need to be acknowledged.

The alarm banner line will still display alarm status.

3.10 Dialog box

The dialog box reports the ongoing state of the DVST unit to the user and includes details of successful calls and also the system identification of any remote stations contacted.

3.11 Built in image storage

The DFT0200 now has a disk drive to record incoming images.

This disk is divided into two partitions:

The first partition comprises a conventional file system with a directory structure.

The second partition acts as a buffer for incoming images.

When the system goes online, images are stored at the next available position on the second partition, overwriting the oldest images stored. In a single session the system can fill the second partition. However, it will not overwrite any of the images in this session.

The remote control handset can be used to replay images from the second partition or to play files from the first partition. All images are recorded with the time and date, remote system ID and alarm status.

3.12 Remote Control (Optional)


Using the remote control handset gives you the facility to copy single images or sequences from the second partition to the first, with a file name. This allows images, for example an alarm sequence, to be saved for future reference.

The handset is similar to a normal VCR remote control handset and allows replay of the second partition, recording of sequences and playback of clipboard files. Standard video playback functions are supported on the second partition i.e. play, stop, pause, fast wind, picture search and single frame advance/rewind.

Directory Listings of the clipboard are available from the remote and playback of the clipboard files is supported. Clipboard files can only be replayed at normal speed with the current version of software and frame advance etc are not supported.

All functions of the handset are “one touch” controls and will continue until another key is pressed.

Key designation



Function
ON/OFF
GOTO

Description

Turns the remote control handset on/off
Go to a specified frame number, this can only be used in Stop mode. The frame number is entered at the “Goto frame number” prompt.

COUNT

Toggle the frame counter on/off. Frame counter is always turned on for: frame advance/reverse/fast forward/rewind/picture search. The counter can be turned on and off on a still frame to avoid masking any of the image. In PLAY mode the counter will be displayed during picture search

F1

No function allocated

CLIP

A Clipboard function is displayed when the key is pressed. The options are: Play Clip, Create Clip and Delete Clip.
Play Clip - Displays a list of existing clips, using the ^ and v keys highlight the desired clip and press Enter. The clip is displayed, all normal control functions are available. Press the Stop key twice to exit from the clip.
Create Clip - Allows a new clip to be created. Selecting frame numbers and Enter will include that frame in the clip. When all frames have been selected highlight “Copy frames to new clip file and press Enter.
Delete Clip - Displays a list of existing clips, using the ^ and v keys highlight the clip to be deleted and press Enter. If a password is set this must be entered to confirm clip deletion.

PLAY

Play stored images from the current index at “normal” speed

PAUSE

Stop and display the current frame

<|

Single frame reverse

|>

Single frame advance

<<

Rewind without displaying images but updating the index counter. Rewind slows down as it gets close to 0 and pauses for 1 second at zero. Rewind will then continue. In PLAY mode this will “picture search” in reverse as fast as images can be read from disk and displayed. PLAY or << buttons cause “normal” playback, >> will switch directly to “picture search” forwards

>>

Fast forward updating the index counter without displaying images. Fast forward slows as it gets close to the end of the disk and then pauses for 1 second. It will then continue at high speed from 0. In PLAY mode this button will give “picture search” forward as fast as images can be retrieved and displayed. PLAY or >> buttons switch to “normal” playback, REW switches directly to “picture search” backwards

REC

No function allocated

NOTE:

PLAY will search for the first available frame after the current frame. When exiting an online session the “current” frame will be the last image stored and PLAY will therefore start from the oldest images on the disk. On a new disk there will be no data after the current frame and PLAY will then search until it wraps around to the start of the disk.

Stopping a PLAY, >> or << will cause the DFT0200 to go to (in order of preference):

(a)The first next image within the following 40K Bytes

(b)The last image in the previous 40K Bytes

(c)The “current” image

Therefore if these functions are stopped on a new machine in a clean part of the image area, the latest or “current” image will be displayed.

4 Installation

The DVST Transceiver is supplied as a desktop unit which can be readily rack mounted using the rack mount kit supplied with each machine.

When used with the 19 inch rack mount kit the DVST Transceiver is 2U in height.

4.1 Rear Panel connections

The DVST Transceiver uses BNC connectors for all video inputs and outputs. Other data connections are made via standard D type connectors. The optional keyboard is connected by a 9 pin D type female plug.

WARNING: DO NOT CONNECT THE UNIT TO OTHER EQUIPMENT WITH POWER ON.




Fig: 2 Rear panel layout

Key to Fig: 2

- | | | | |
|------------------|------------------|---|---------------------|
| 1 Monitor inputs | 5 Aux 1 port | 9 Aux 0 port | 13 Power Connection |
| 2 Camera Inputs | 6 Remote control | 10 Alarm port | |
| 3 Aux 3 port | 7 Keyboard port | 11 Modem port | |
| 4 Aux 2 port | 8 X.21 ports | 12 VCRIN/OUT connections(Not operational) | |

4.2 Power Inputs

The DVST Transceiver is powered via a standard mains IEC cable which plugs into the rear panel.

The power supply is self adjusting to the mains input and can accept a voltage from 90 to 260 volts.

Mains supply frequency can be either 50 or 60 cycles.

4.3 Monitor Outputs




Fig: 3 Monitor connections

The Monitor is connected to the MON A socket and should be terminated at 75 ohms. Most monitors have a switch at the rear that should be set to `LOW`, `ON` or `75ohm` as opposed to the `Hi Z` or `OFF` position.

As the Monitor will be displaying multi-screen compressed pictures the monitor should have at least a 12 inch screen. For comfortable desktop operation a 14 inch monitor is recommended.

4.4 Setting up the Monitor

Most of the time the Monitor will be displaying the digital output from the DVST Transceiver. Some monitors may have part of the digital picture off the screen. This is due to the monitor overscanning.

The DVST unit has been designed to display the digital picture centrally on a studio standard monitor with no overlap at the edges of the screen.

If the main monitor cannot display the digital picture without losing information at the edges of the screen, then the monitor is out of adjustment and should be realigned.

Most monitors have overall width and height controls located internally. This adjustment is simple but due to the high voltages present in monitor circuits this alignment should only be entrusted to qualified personnel.

Warning: Voltages at the rear of a monitor can be in the region of 25,000 volts and the greatest care must be taken when working on this type of equipment. Remember these voltages persist even after the monitor has been turned off.

4.5 Alarm Outputs

Figure 4 displays the alarm output connections on the DFT-0200.




Fig: 4 Alarm output connections

5 Setup (Basic)

5.1 General

Setup of the DVST DFT-0200 is undertaken either using the keyboard or a PC (Personal Computer) connected to the AUX 3 port on the rear of the unit.

The setup mode is entered by pressing the **<SETUP>** key on the keyboard. The DVST screen will go blank and the command prompt **CMD>** will appear on screen. The DVST is ready to accept direct commands from the keyboard or PC.

If a PC is being used, with a communications program, local setup mode can be entered by typing “**+++ <ENTER>**” on the keyboard. The DVST commands will also appear on both the screen of the PC and the system monitor.

If a password has been set the screen will go blank and the prompt **PASSWORD>** will appear on the screen and a valid password must be entered followed by pressing the **<ENTER>** key. If this entered correctly the prompt **CMD>** will appear on screen. More details on the operation of passwords appear later in this manual.

Typing **HELP** and pressing the **<ENTER>** or return key will list all the available DVST commands. These are listed with brief descriptions to assist users familiar with set up of the DVST. All these commands are explained in detail within the manual, and have been grouped in a logical order to make set up of the DVST easy.

Typing **VIEW** and then pressing **<ENTER>** will list the present settings of the DVST.

To exit the **SETUP** mode type **QUIT** then **<ENTER>**. The DVST will then return to normal operation.

5.2 Set up via keyboard

When the setup mode is entered the normal operation of the keyboard is suspended and the keyboard becomes alpha numeric.

The keys A to Z will initially generate upper case letters. Use the **<HOLD>** key toggle Upper / Lower case letters. The lamp on **<HOLD>** key is **on** for Upper case letters and **off** for lower case letters.

Note: The **<HOLD>** key is a toggle on / off type operation and hold should not be held down while typing on other keys.

Some *special characters*: () / \ ; ; \$ % ? ! = ~ - + ^ , appear on alpha keys. These can be accessed by first pressing the <ALT> key (also marked AUX 1) the keylamp will illuminate to indicate that the next key pressed will send a *special character*.

Once the key has been pressed and the *special character* sent, the keylamp on the <ALT> key goes off and the keyboard will generate normal characters.

To send another *special character* the process must be repeated.

Numeric keys generate numeric characters as normal.

The blank space character is generated by the <F1> key and the ampersand “&” is generated by the <F2> key. Full stop is <F3> and comma is <F4>.

The <F5> key is DELETE and will erase typed characters from right to left.

The <F6> key operates as ESCAPE.




Fig: 5 PC Connections

5.3 Remote Setup

Remote DVST units can also be set up in the same manner as a local DVST. The same procedure should be followed when the DVST is on line to a remote unit. When the SETUP key is pressed the screen will go blank and the command prompt **REM>** will appear on screen.

Proceed as for the local system.

Note: A PC cannot initiate remote set up with the “+++” command.

5.4 DVST Commands

Most commands are typed in direct and terminated by pressing the <ENTER> key on a PC or the key marked **ENT** on the extension keyboard.

HELP *Lists all commands available.*

Note: Paragraphs 4.6 onwards detail the command information listed by the help option and have been grouped together in the logical order that should be used when setting up a DVST system.

QUIT *Exits the SETUP mode.*

This returns the DVST to normal operation.

RESET *Resets DVST to factory defaults*

This command is used to completely reset the DVST system.
(All values are reset to their default values.)

Note: These values are stored in an integrated circuit called an EEPROM. This is not dependent on a battery backup and will retain its settings indefinitely without a power supply.

VIEW *Display current DVST settings*

This will display all the current DVST settings.

5.5 Define Camera Inputs

MAX=nn *Sets maximum number of cameras
(default, 8)*

Range is 1 to 16.

Correct settings of this ensures that any receiving station does not spend time trying to collect invalid camera inputs.

COL=nn *Set camera to Colour*
MON=nn *Set camera to Monochrome
(default, all cameras set to colour)*

Format is COL=01, COL=05 etc.

Format is MON=06, MON=15 etc.

It is important that camera inputs are correctly defined as colour or monochrome.

CAMnn= *Set camera title nn to ...
(default, Camera 01=CAMERA 01 etc.)*

Format is CAM01=FRONT DOOR

Auxiliary Ports

The following is a short form of PORT command to set the AUX3 mode. The auxiliary port on the DVST can be used for programming the DVST with a PC or for generating printer reports. Protocol is RS232 8 characters, no parity, one stop bit, default at 9,600 baud.

AUX= *Set AUX port usage: **TERM, PRINT, MCI, DTMF, ENG, NULL**
(default, TERM)*

TERM is for terminal operation, control by PC

PRINT operates as a printer connection

MCI is for machine control

DTMF sends telemetry codes to the port

ENG displays the debug messages

NULL Turns the port off

Note: Altering this command from a PC is valid, but after changing the setting on the PC it will no longer communicate with the DVST. The reason is that the port has now been assigned a different task. The keyboard can be used as normal and also to set the port back to terminal operation.

5.6 Define Auxiliary Ports 1, 2, 3

The auxiliary ports 1, 2, 3 on the DVST can be configured to operate with additional equipment i.e. printers, telemetry equipment and PC based control systems (MCI).

PORT=

Set PORT usage,

(Each field entry is separated by a space. If the commands are entered correctly the new settings will be displayed):

**<AUX PORT> <BAUD RATE> <PARITY>
<DATA BITS> <STOP BITS> <FORMAT>**

(default settings)

AUX1 38400 N 81 PKT

AUX2 38400 N 81 DATA

AUX3 9600 N 81 ENG

AUX PORTAUX, AUX1, AUX2, AUX3

BAUD RATE1200, 2400, 4800, 9600, 19200, 38400

PARITYN (None) O (Odd) E (Even)

DATA BITS5, 6, 7, or 8

STOP BITS1 or 2

FORMAT

Aux1	DATA	Character based inband data operation
	PKT	Packet based inband data operation
	BLK	Block inband data operation
	NULL	Turn off port
	MODEM2	Set port 1 to modem mode

Aux2	DATA	Character based inband data operation
	NULL	Turn off port

Aux/ Aux3	DTMF	Send telemetry codes to port
	ENG	Display debug messages
	NULL	Turn off port
	TERM	Terminal operation
	PRINT	Serial printer connection
	MCI	Machine control interface

Example

PORT = Aux3<space>9600<space>N<space>8<space>1<space>Term <return>

6 P.C. Operation

6.1 Set up via PC

To set up the DVST using a PC you will need the following:

A personal computer with an RS232 port.

A connection cable between the serial port of the computer and the serial port (AUX3) of the DVST unit. (Details are in the cable section of this manual)

A suitable communications program for your PC that can operate at 9,600 baud.
i.e. Procomm.

Procedure:

Turn off the power supply to the DVST and the PC.

Connect the two units together using a serial cable.

Power up both DVST and the PC then start the communication program.

Make sure that the speed and protocol of the communications program are as follows:

Baud Rate=9600

Parity=None

Data Bits=8

Stop Bits=1

6.2 PC and Printer Connection

Connection to a PC serial port or a printer requires a 9 to 9 cable. Some PCs and Printers use a 25 pin connector. Adaptors can be easily sourced if needed.

This page intentionally blank.

7 Demonstration Mode

This is provided to allow two DVST units to be connected back to back without the need for connection to MODEMs or Terminal Adapters.

A special demonstration cable is used, details of this are explained later in the chapter.

7.1 Demonstration mode

DEMO= *Turn the demonstration mode ON / OFF*

Turns the demonstration mode on or off.

EXTCLK= *Select demonstration speed, 1 to 6
(default, 6)*

This command selects the synchronous transmission speed used in the demonstration mode.

- 1 external clock = 9600 baud
- 2 external clock = 14400 baud
- 3 external clock = 19200 baud
- 4 external clock = 38400 baud
- 5 external clock = 56000 baud
- 6 external clock = 64000 baud

Note: Two demo cables can be used to simulate dual ISDN operation.

7.2 Demo Cable

This cable allows two DVST units to be connected back to back without the need for connection to MODEMS or Terminal Adapters.




Fig: 6 Wiring details for demo cable

Tech Note:

This is a synchronous balanced transmission. Transmit and receive lines therefore cross yet maintain polarity. The flying lead is used to source a clocking signal from the MODEM port.

7.3 Connecting the demo cable

Single cable operation

The cable connects PORT 0 on the transmit unit to PORT 0 on the receive unit. The small flying lead connects to the MODEM port on the receive unit.




Fig: 7 Demo cable connections

Dual cable operation




Fig: 8 Demo cable connections - dual mode

The first cable connects PORT 0 on the transmit unit to PORT 0 on the receive unit. The small flying lead connects to the MODEM port on the receive unit.

The second cable connects PORT 1 on the receive unit to PORT 1 on the transmit unit. The small flying lead connects to the MODEM port on the transmit unit.

8 Modems

8.1 PSTN Connection (Modem)

Connection to a PSTN telephone line is via a modem and modem port.

8.2 MODEM Commands

MODEM= *Sets MODEM operation, three parameters:*

The MODEM= command controls three distinct parameters.

OFF
(default, OFF)

Tech note: The reason is as follows; if set to ATMODE the DVST attempts to communicate with the MODEM when starting up, exiting set up mode etc. The DVST will wait a set period of time for replies before giving up. This will considerably slow the system if no MODEM is attached.

DIRECT, ATMODE
(default, ATMODE)

The DIRECT mode is used if the MODEM has its telephone numbers stored internally and the DVST does not pass telephone numbers for dialling.

The ATMODE is most often used. The DVST passes numbers from the dial menu to the MODEM which then initiates a call.

SYNC

The sync or synchronous mode relies on the modem generating clock signals to the DVST.

MODEM

Modem switches from the command mode **CMD>** to allow direct control of a connected MODEM. The speed of communication with the MODEM will be as set with the **MBAUD=** command.

This is called transparent MODEM mode and is terminated by pressing the ESCAPE or ESC key.

MBAUD= *Set MODEM port ASYNC baud rate.
(default, 19200)
9600, 19200, 38400*

This command sets the speed of communication between the DVST and the MODEM when in the asynchronous mode. The speed of communication in the Synchronous mode is determined by the clock signal supplied by the MODEM.

ASYNC

In the asynchronous mode the MODEM controls the flow of data using RTS/CTS signals.

MODEM2

Modem switches from the command mode **CMD>** to allow direct control of a connected MODEM through AUX 1. The speed of communication with the MODEM will be as set with the **PORT=** command.

This is called transparent MODEM mode and is terminated by pressing the ESCAPE or ESC key.

PORT= *AUX1, 19200, N 8 1, MODEM2*

Refer Chapter Setup (Basic).

8.3 Modem configuration strings

All MODEMs need special configuration, depending on how the MODEM is to be used and how the DVST will interact with it.

Standard MODSTR set ups configure the MINIT and SREG strings, the USER string is left free for any extra configuration that may be needed.

MODSTR= *Set type of modem: **FAST** or **SYNC**
(default, FAST)*

This setting (shortened form of MODem STRings) automatically sets up the DVST to operate with one of the three recommended MODEMs.

FAST

This sets the MINIT and SREG strings for correct synchronous operation with the MOTOROLA 326x VFAST MODEM. The MODEM configuration strings are set up as follows:

```
MINIT=AT&M1 &D2 &C1 *FLO *AA1 *DTO *OC1
SREG=ATS10=30S25=0
```

SYNC

This sets the MINIT and SREG strings for correct synchronous operation with the MICROCOM 4232bis MODEM. The MODEM configuration strings are set up as follows:

```
MINIT=AT&M1 &D2 \GO \EO E1 &C1 \JO
SREG=ATSO=1
```

MOD2STR= *Set type of modem: **FAST**, **SYNC**, **ASYNC** or **ZYXEL**
(default,)ASYNC*

FAST

This sets the MINIT and SREG strings for correct synchronous operation with the MOTOROLA 326x VFAST MODEM. The MODEM configuration strings are set up as follows:

```
M2INIT=AT&M1 &D2 &C1 *FLO *AA1 *DTO *OC1
SREG2=ATS10=30S25=0
```

SYNC

This sets the MINIT and SREG strings for correct synchronous operation with the MICROCOM 4232bis MODEM. The MODEM configuration strings are set up as follows:

```
M2INIT=AT&M1 &D2 \GO \EO E1 &C1 \JO  
SREG2=ATSO=1
```

ASYNC

This sets the MINIT and SREG strings for correct asynchronous operation with the Trailblazer MODEM. The MODEM configuration strings are set up as follows:

```
M2INIT=ATSO=1 &C1 &K3 E1 V1 &MO  
SREG2=ATS7=60 S10=7 S37=7  
~S50=255 ~S51=5 ~S52=1 ~S110=0 ~S104=0
```

ZYXEL

This sets M2INIT and SREG2 for the correct synchronous operation with the ZYXEL modem. The modem configuration strings are set up as follows:

```
M2INIT=AT&M1&D2&C1&H0  
SREG2=ATS10=30 S0=1
```

USER=... *Available for user configuration
(Default, blank)*

The USER string is for any extra commands that the user may need to send to the modem in addition to the MINIT and SREG settings.

SEND *Send current modem configuration*

This transmits the information contained in the MINIT, SREG and USER strings to the MODEM.

Although this command can be issued from the command mode at any time, it is also invoked at the termination of any call and when the command mode is exited with the QUIT command.

DIAL=

*Modem dial string
(default, ATDT)*

This is the command that must precede all numbers that the MODEM has to dial. Typically the MODEM will dial using either pulse or tone dialling. This is dependent on the telephone exchange the MODEM is connected to, most modern exchanges are able to accept tone dialling which is faster than the older pulse dialling method.

For tone dialling: DIAL=ATDT

For pulse dialling: DIAL=ATDP

Tip: Extra information can be linked to the above commands, internal exchanges that require a "9" to be dialled to access outside lines can have this added to the dial string, typically ATDT9.

8.4 Modem Operation

All modern modems respond to a set of "Hayes" commands. There are several differences in these commands from manufacturer to manufacturer. It is important to use the correct commands with each modem and not to attempt to use one manufacturer's set up with another manufacturer's modem.

If possible modems should be linked to DVST in the synchronous mode. Some modems, for example those using PEP (Packet Ensemble Protocol), can only be used in the asynchronous mode.

Cables for connection to synchronous and asynchronous modems are different and are not interchangeable. Refer to the Cable Assemblies chapter for further details.

8.5 Connecting a modem in direct mode

This mode uses a modem in a 'dumb' mode, and purely relies on the hardware control lines. Telephone number selection, and all other configuration must be performed at the modem.

The modem is controlled using DTR (Data Terminal Ready), and indicates it's status using DCD (Data Carrier Detect).

Note: This mode is not recommended, easier operation is achieved in **ATMODE**.

Call request

A call is requested by making DTR active (high). At this point the MODEM dials it's stored number, and attempts to establish the call with the remote end. When the call connect has been completed the modem raises it's DCD line, confirming it is connected with the remote location.

A call already being active is indicated by the DCD line being active (high) from the MODEM.

Call answer request

If a call is incoming, the modem answers the call, establishes the physical link, and then raises DCD to inform the DVST unit that a call is present. The DVST unit responds to this by taking DTR active (high).

Call disconnect.

This is requested by dropping the DTR signal. A successful disconnect is confirmed by the DCD line being dropped by the MODEM. In this mode the DTR line remains low.

Configuration of modem in direct mode

No configuration can be performed by the system, however the following are required of the modem :

- Select synchronous operation.
- Dial stored number on low to high transition of DTR.
- Disconnect on a high to low transition of DTR.
- DCD must follow remote carrier.
- Ignore DTR to answer.
- Auto-answer. (If required).
- No flow control enabled.

8.6 Using a modem in ATMODE

In this mode the Hayes set of commands is used, all of which begin with the letters AT.

Both call setup and configuration are performed using these commands.

The commands can be configured on the DVST unit in setup mode.

The modem is also controlled using DTR (Data Terminal Ready), and indicates it's status using DCD (Data Carrier Detect).

Call request

The DTR is normally active, unless the modem channel is turned off, or the unit is in setup mode.

To dial a call the system sends the dial string (set by DIAL= in the DVST setup menu) to the modem, followed by the number selected.

For synchronous operation the modem switches to synchronous mode on connection. When the call connect has been completed the modem raises it's DCD line, confirming it is connected with the remote location. A call already being active is indicated by the DCD line being active (high) from the modem.

Call answer request

If a call is incoming, and the DTR line is high, the modem answers the call, establishes the physical link, and then raises DCD to inform the DVST unit that a call is present.

Call disconnect

This is requested by a high to low transition on DTR. A successful disconnect is confirmed by the DCD line being dropped by the modem.

In this mode the DTR returns high after a short delay.

8.7 General settings for modems in ATMODE

The modem is configured from the DVST unit using the following strings:

MINIT=general modem configuration.

SREG=typically used for setting of s-registers.

USER=optional string, typically for individual customisation.

DIAL=string used to dial, typically ATDT for tone dialling.

The configuration details stored in MINIT, SREG & USER are sent on power-up, leaving setup mode, and on disconnecting a call. If a MODEM is not present a large delay will be experienced while the system waits for replies from the MODEM. To avoid this the command MODEM=OFF should be selected from the DVST setup menu. It is also possible to transmit or send these values to the MODEM using the SEND command in setup.

It is also possible to communicate with the modem directly using the MODEM command.

MODEM Requirements

Although there are default settings for three MODEMs, other MODEMs can be configured to operate with DVST.

As the settings vary from manufacturer to manufacturer there is not a set series of commands that are guaranteed to work. The following tables detail possible configurations, all should be checked against the MODEM manual. Before attempting these suggested settings the MODEM should be reset to factory defaults with the command AT&F or ATZ

The following settings are required as a minimum:

All modems:

Action required of MODEM	Possible AT settings
DCD (Data Carrier Detect, sometimes abbreviated to CD) must be set to follow the carrier. This signal indicates to the DVST that a connection to another unit has taken place.	&C1
The call must disconnect on a high to low transition of DTR (Data Terminal Ready). Only answer a call if DTR is present.	&D2
Auto-answer may be set if required.	S0=1 Check MODEM manual Country specific
Echo commands.	E1

Synchronous Modems:

Extra action required of Synchronous MODEM	Possible AT settings
Asynchronous mode must be set to dial the number and the modem must switch to synchronous mode on carrier detect.	&M1
Flow control must be disabled.	&K0 Check MODEM manual
The modem should ignore RTS.	&R1

Asynchronous Modems:

Extra action required of Asynchronous MODEM	Possible AT settings
Asynchronous mode must be enabled.	&M0
Flow control must be enabled on RTS/CTS.	&K3
Error correction enabled (if needed).	Refer to MODEM manual

Note

It is strongly recommended that once the modem has been configured as above, it is set in such a mode that this configuration is recalled automatically on power up. This will help to ensure correct operation after a power failure. Consult you modem instructions for details of how to achieve this.

8.8 MOTOROLA VFAST

Cable required to connect to DVST: (25 to 25 - V24 SYNC)

When installing the VFAST MODEM the following procedure should be followed:

Connect the MODEM and DVST as in the installation chapter.

Power up the DVST (leave the MODEM without power).

Enter the setup mode and configure the DVST for operation with the VFAST MODEM by typing the command `MODEM=ATMODE,MODSTR=FAST` (default setting).

Power up the MODEM and wait for the self test to finish.

Type SEND then <ENTER>.

The DVST will program the MODEM.

It is good practice to store these values permanently in the MODEM.

Then the values will not be lost if power is removed from the MODEM.

To store these values proceed as follows:

Type: `MODEM <ENTER>`

Type: `AT <ENTER>`

Type: `AT&Y1&W1 <ENTER>`

Type: `<ESC>`

The MODEM will then always power up with the correct operational configuration.

Country specific settings

The answer on number of rings command `*AA1` is not valid in some countries (France, xx) and the MINIT string should be reprogrammed with the value `*AA2`.

The MINIT string is programmed as:

`MINIT=AT&M1 &D2 &C1 *FLO *AA2 *DE12 *OC1`

No Dialtone

In some cases the MODEM will not recognise the presence of a dial tone from the exchange. The following codes will allow blind dialling and if these are needed permanently they should be followed by AT&W1 to store these settings.

ATX3 Dial blind without presence of dial tone

AT*BD0 Wait two seconds before dialling

AT&W1 Store above settings in option 1

Note: This feature is country specific and may not be available in some versions of the MODEM's software. Please refer to the literature supplied with your MODEM.

Transmission speed

The MODEM can be a little ambitious in setting the line speed. It is likely that a link will be established at a higher speed than the line can support without an unacceptable level of errors.

In these cases it may be necessary to limit the speed of transmission until a reliable point is reached.

Maximum line speed may be set by the command:

AT*MXn

where the following baud rate applies:

n=1124,000

n=1021,600

n=919,200

n=816,800

n=714,400

n=612,000

n=59,600

n=47,200

n=34,800

n=22,400

n=11,200

n=0300

To limit the speed of transmission to 14,400 use **AT*MX7**. This could be stored in the USER= string.

8.9 Microcom V3242

Cable required to connect to DVST 25to25 (Part No.AS-DVST-SYNC)

Synchronous mode :

&M1Dial async, switch on connect.

&D2Hangs up with on to off transition of DTR - needed for auto answer.

\G0Disables modem flow control.


\E0Do not echo data !

E1Echo commands.


&C1CD follows carrier.

\J0Turn off baud rate adjust.

DIP Switch Settings Synchronous Operation




Front panel switches




Rear panel switches

Cable required to connect to DVST 9to25 (Part No. AS-DVST-ASYNC)

DIP Switch Settings Asynchronous Operation



Front panel switches



Rear panel switches

8.10 Trailblazer

Cable required to connect to DVST 9to25 (Part No. AS-DVST-ASYNC)

Async mode

Trailblazer in Conventional Command mode.

&C1CD follows carrier.

&k3RTS/CTS flow control.

E1Echo commands

V1Textual result codes

&M0Async mode

s7=60Wait 60 seconds for carrier.

s10=7Carrier loss to disconnect time.

s37=7Attempt to connect in PEP mode.

~s50=255Operate in PEP mode.

~s51=519200 bps operation.

~s52=1Modem hangs up on DTR, only autoanswer on DTR.

~s110=0PEP data compression disabled.

~s104=0Disable auto dialling.

8.11 OCTOCOM OSI 8196A

Cable required to connect to DVST 25to25 (Part No. AS-DVST-SYNC)

Manufacturer:

Octocom Systems, Inc.
One Executive Drive
Chelmsford,
MA 01824
USA

No DIP switches are used.

A single DATA push button on the front panel serves to unhook the modem.

When the modem is unpacked and used for the first time the CD line is held on. This means that the DVST unit believes that there is an incoming call and waits for data.

Proceed as follows to clear this condition:

Wait for the DVST unit to time out

and then press **<SETUP>**

At the command prompt CMD> type **MINIT= <RET>**

At the command prompt CMD> type **SREG= <RET>**

At the command prompt CMD> type **USER=AT <RET>**

At the command prompt CMD> type **SEND <RET>**

Wait for the information to be sent to the modem.

At the command prompt CMD> type **MODEM <RET>**

The unit will reply - Modem Mode

Type **AT <RET>**

The reply from the modem is "OK"

Type in the following, **AT&M1&C1&D2&K0&R1<RET>**

The reply from the modem should be "OK", if the reply is "ERROR", try again.

Type **AT&W**

The modem will now power up without the CD line held on.

Press the **<ESC>** key to exit modem mode.

At the command prompt CMD> type. **MINIT=&M1 &C1 &D2 &K0 &R1.**

&M1Dial async, switch to sync on connect.

&C1CD follows remote carrier.

&D2Hangs up with on to off transition of DTR - needed for auto answer.

&K0Modem flow control is disabled.

&R0Modem ignores RTS, CTS is on when the modem is online.

9 Terminal Adapters

TA(s) or Terminal Adapters allow the DVST to communicate over digital ISDN telephone lines.

9.1 ISDN Connection (Terminal Adapter)

Connection to an ISDN line is via a terminal adapter and Port 0. On systems using dual ISDN lines both Port 0 and Port 1 should be connected.

The type of cable required to connect to the terminal adapter can vary.

DUALISDN= ...Sets dual ISDN support **ON** or **OFF**
(default, on)

ISDN= ...Sets ISDN for **ATMODE**, **DIRECT**, **X21** mode
(default, **DIRECT**)

DIRECT

DIRECT mode relies upon the terminal adapter dialling a stored number or a network only accessing a single remote point. Also used for Demo mode (chapter 7)

ATMODE

ATMODE refers to Hayes AT dialling where the numbers to be dialled are stored in the DVST dialling menu.

X21

Uses X21 dialling for numbers in the DVST menu

Connection can be made in the direct mode, where the number to be called is stored in the terminal adapter, or in the X21 dialling mode where the DVST passes the number to be dialled to the Terminal Adapter, or ATMODE.

V35

V35=ON/OFF

Applicable in all modes (ATMODE, DIRECT and X21)

9.2 Connecting a terminal adapter in direct mode

This uses the signalling lines; C (control) and I (indicate), to respond to and initiate calls.

Making a Call

The DVST initiates a call by raising C

The TA then dials its stored number

When the call is connected the TA raises I

Call continues

Answering a Call

The TA indicates an incoming call by raising I

The DVST responds by raising C

Call continues

Call disconnection

The DVST ends a call by dropping C

The TA confirms disconnection by dropping I

Configuring a Terminal Adapter for direct mode operation

As the control lines I & C are used to control calls, the following is required of the system:

Answer : C

Originate : C

Disconnect : C

Alerting : I

DCD/I : Delay

Note:

The above settings are the basic requirements. TAs have many other settings which can affect transmission such as speed of call, type of call, circuit switch etc.

9.3 Gandalf TA1

Cable required 15 to 25 (2 of Part No. AS-DVST-TA1)

The Gandalf TA1 is a dual port unit capable of simultaneously using both ISDN B channels on an ISDN2 connection.

The Gandalf has two X21 ports, PORT0 & PORT1. They must be configured as follows for DIRECT connection:

Direct Connection

Configure the Gandalf as follows:

CALL MODE=CKT SWITCH AUTO

CALL TYPE=BOTHWAY

CALL SPEED=NEGOTIATE

ANSWER=C

ORIGINATE=C

DISCONNECT=C

ALERTING=I

DCD/I=DELAY

9.4 ASCOM 5000 / CITAM

ATMODE

Cables required - 2x 15 to 15 (Part No. AS-DVST-X21)

Dip switch settings can be used and should be set as follows:




Fig 9: ASCOM internal dip switch settings (ATMODE)

Note: Switch 3 selects the sub address, if used.

Step	Instruction	Remarks
1	Using the pull handle, remove the circuit board module from the Citam 5000	
2	Adjust the dip switches as shown in Figure 9	The Citam will now perform a self test. On completion the display will read ISDN .
3	Press the select key four times so that the legend `CONF` appears on the display.	
4	Press the enter key once and it will say `PRT1` , press the select key twice it will say `TA` , press the enter key it will say `SHOW` .	
5	Press and hold select until the display reads `CHNG` , remove your finger from the select key and press the enter key, `INDB` will be displayed.	
6	Press the enter key, the message will be `ON` , use the select key to turn this to `OFF` , then press the enter key.	
7	Hold the select key and press the enter key, the display will return to `CONF` .	This has turned of the in-band test feature of the unit.
8	At `CONF` press the enter key, the display will read `PRT1` for port 1.	

Step	Instruction	Remarks
9	Press the enter key, it will read `SHOW` . Hold the select until this changes to `CHNG` , press the enter key, display will then show `DIPS` for dip switch.	
10	Press the enter key, it should read `INAC` for inactive, press the select key to change this to `ACTV` for active, press the enter key to return to `DIPS` .	
11	Hold the select key down and press the enter key, this will return unit to `CONF` .	
12	Press the enter key and the display will read `PRT1` , press the select key to change this to port 2.	
13	Press the enter key and `SHOW` will appear, hold the select key for three seconds, the display will change to `CHNG` .	
14	Press the enter key it will change to `DIPS` , press the enter key and it will say `INAC` , press the select key and `ACTV` will be displayed, press the enter key and display will return to `DIPS` .	
15	Hold the select key and press the enter key, returning the display to `CONF` .	The unit has now had the dip switches made active on both ports 1 and 2.

SEND CONFIGURATION STRING

16	<p>At the command prompt CMD> type ISDN=ATMODE <RET> DUALISDN=ON <RET> ISDNSTR = CITAM <RET> At the command prompt CMD> type SEND <RET> Wait for the information to be sent to the modem. At the command prompt CMD> type ISDN0 <RET> AT<RET> AT&W<RET>, <ESC> ISDN1<RET AT<RET> AT&W<RET> <ESC> QUIT <RET></p>	These commands are entered using Setup Mode on the DVST0200 unit via a PC. Refer to Chapter para
----	---	--

The Citam is configured to operate on DVST.

X21

Cables required - 2x15 to 15 (Part No. AS-DVST-X21)

Dip switch settings can be used and should be set as follows:


Switch Position

Fig 10: ASCOM internal dip switch settings (X21)

Note: Switch 3 selects the sub address, if used

Step	Instruction	Remarks
1	Using the pull handle, remove the circuit board module from the Citam 500	
2	Adjust the dip switches as shown in Figure 10	The Citam will now perform a self test On completion the display will read ISDN
3	Press the select key four times so that the legend `CONF` appears on the display	
4	Press the enter key once and it will say `PRT1` , press the select key twice it will say `TA` , press the enter key it will say `SHOW`	
5	Press the hold select until the display reads `CHNG` remove your finger from the select key and press the enter key, `INDB` will be displayed	
6	Press the enter key, the message will be `ON` , use the select key to turn this to `OFF` , then press the enter key	
7	Hold the select key and press the enter key, the display will return to `CONF`	This has turned off the in-band test feature of the unit
8	At `CONF` press the enter key, the display will read `PRT1` for port 1	

Cont.

Step	Instruction	Remarks
9	Press the enter key, it will read `SHOW` . Hold the select until this changes to `CHNG` , press the enter key, display will then show `DIPS` for dip switch	
10	Press the enter key, it should read `INAC` for inactive, press the select key to change this to `ACTV` for active, press the enter key to return to `DIPS`	
11	Hold the select key down and press the enter key, this will return unit to `CONF`	
12	Press the enter key and the display will read `PRT1` , press the select key to change this to port 2	
13	Press the enter key and `SHOW` will appear, hold the select key for three seconds, the display will change to `CHNG`	
14	Press the enter key it will change to `DIPS` , press the enter key and it will say `INAC` , press the select key and `ACTV` will be displayed, press the enter key and display will return to `DIPS`	
15	Hold the select key and press the enter key, returning the display to `CONF`	The unit has now had the dip switches made active on both ports 1 and 2

The Citam is configured to operate on DVST.

9.5 Dataflex TA

The Dataflex terminal adaptor

Cable 2 x 15 to 15 way (X21 Cable Assembly refer to page)

These commands are entered using Setup Mode on the DVST0200 unit via a PC (Refer to Chapter para)

SEND CONFIGURATION STRING

1At the command prompt **CMD>** type

ISDNSTR =DATAFLEX <RET>

At the command prompt **CMD>** type

ISDN=ATMODE <RET>

Wait for the information to be sent to the modem.

At the command prompt **CMD>** type

DUALISDN=ON <RET>

SEND <RET>

ISDN0 <RET>

AT <RET>

AT&W <RET>

<ESC>

ISDN1 <RET>

AT <RET>

AT&W <RET>

<ESC>

At the command prompt **CMD>** type

QUIT <RET>

The Dataflex TA is now configured for use with the DVST0200.

10 Calls

10.1 Passwords

Passwords can be set and used by the system. When a PASSWORD is set it provides protection for the system at two points:

- 1) Whenever a remote system calls it must send the correct password, otherwise no connection will be established.
- 2) Whenever the SETUP key is pressed, the password will be requested before the setup mode is entered.

Method:

Enter SETUP mode is by pressing the SETUP key on either keyboard.

If a password has been set the screen will go blank and the prompt PASSWORD will appear on the screen. At this point a valid password must be entered followed by pressing the <ENTER> key. If this entered correctly the prompt CMD will appear on screen.

PASSWORD= *Set system password to ...*

The system password can be up to 10 alpha numeric, case sensitive, characters.

Once this has been set only calling units that have the associated password linked to the telephone number can access the system.

PASSn= *Set telephone entry n password to ...
Range is 0 to 9 (passwords not available 10-19)*

This is linked to the designated telephone number and is the keyword that will unlock the remote system that is being called. It may be up to 10 alpha characters in length.

Format: **PASS4=BERLIN**

In the above case the system called would have the password set to BERLIN. Only then could the system be accessed.

Default: None set

SPASSWORD= *Set SETUP password to ...*

This feature allows an additional password to be allocated just to provide security for the set up mode. This can be used to prevent a remote user accessing the system and altering the settings.

Default: None set

Note: To maintain security, passwords cannot be read back from the system. Care should be taken to ensure passwords are not lost as this will require a new EEPROM chip to be fitted to the DVST.

10.2 On Screen Titling

SYSTEM= *Set system ID string to ...*

This is a 40 character title which appears on the front screen of the DVST. When a transmitter sends to a receiver this title is transferred from the transmitter and appears on the baseline of the receiving monitor.

TIME= *Set current time in HHMM format*

The time is based on the 24 hour clock. 4 digits must be entered.

DATE= *Set current date in DDMMYY format*

Date is always set as a six figure format.

Two optional messages are superimposed on camera images sent from the transmitter. The first is the camera title and the second is the time and date.

TLPOS= *Set camera title position
(default, 1)*

When the images are transmitted the camera title appears at the top of the screen. This setting adjusts the height of the camera title.

TDPOS= *Set clock screen position
(default, 11)*

When the images are transmitted the time & date appears at the bottom of the screen. This setting adjusts the height of the time & date information.

Note: The range available for both TLPOS and TDPOS is from 1 to 11, 1 is at the top of the screen and 11 at the bottom. Settings for TLPOS and TDPOS should be 2 numbers apart to avoid overlap. Setting either value to 0 removes the text from the screen.

10.3 Telephone Number Entries / Connection Commands

TELn= *Set telephone entry n to ...
(default, blank)*

Twenty telephone numbers can be stored in memory.

Format: TEL2=01044617944965

If the MODEM or ISDN Terminal Adapter is to work in the DIRECT mode, the entry can be left blank.

Telephone number 0 is the default number dialled when alarms are used to initiate a call to another system. The fall back number if this is engaged is always stored in telephone number 1.

Where a number is used with dual ISDN dialling it is automatically linked with that number plus 10. Therefore Tel number 4 & 14 would be dialled if dual ISDN was selected for that telephone number.

TELn *Set telephone entry n as current*

This selects the number that will be dialled initially if the up/down keys are not used to select another.

Format: TEL2

TYPEn= *Set telephone entry type to dial via **ISDN0, ISDN1, ISDNx2 (dual), MODEM or MODEM2**
(default, ISDN0)*

Each of the telephone numbers can be linked to either a PSTN MODEM or an ISDN terminal adapter.

This command determines which of the external ports (MODEM, MODEM2, ISDN Port0, or ISDN Port1) will be used when a particular telephone number is selected.

Format:

TYPE3=MODEM

TYPE0=ISDN0

TYPE1=ISDN1

TYPE2=ISDNx2

TYPE4=MODEM2

TIMER= *Call connection timeout period
(default, 60 seconds)*

This is the period of time that the DVST will wait while trying to connect a call. This will vary depending on the type of call (ISDN or PSTN) and as there may be a delay in establishing International calls, the timer value should be increased.

DIALCLR= *...Sets time dial menu remains on screen
(default, 30 seconds)*

10.4 **Callback**

This feature allows an operator to dial a remote unit and then have that unit automatically call the operator back. This can be a useful security feature. The operation of callback is as follows:

Local unit calls remote unit.

Call connects.

Local unit passes the dial menu number (0 to 9) that the remote unit will call back.

Call disconnects.

The local unit waits for a return call.

Remote unit waits for ten seconds then calls local unit.

Local unit answers and contact proceeds as normal.

CALLBACK= *Set call back **ON** or **OFF**
(Default, off)*

When the callback feature is switched on the option appears on the dialling menu to make either a normal call or a remote callback call.

Normal call is the default and this is highlighted. By using the left and right arrow keys remote callback can be selected and deselected.

MYMODEM= *Set modem call back number
(default, 0)*

When a local unit calls via MODEM with a remote callback request, this is the dial menu number that the transmitter will attempt to call back via MODEM.

Format: MYMODEM=x

where x is 0 to 19 and selects tel no. 0 to 19

MYISDN0= *Set ISDN call back number
(default, 0)*

When a local unit calls via ISDN with a remote callback request, this is the dial menu number that the transmitter will attempt to call back via ISDN.

Format: MYISDN0=x

where x is = 0 to 19 and selects tel no. 0 to 19

Note: ISDN0 indicates X21 port 0 is used.

11 Images and Transmission

Screen display - Periscope mode

CAMLO=Sets low resolution cameo operation:

Options are:

QUADHI High resolution quad size image
QUADLO Low resolution quad size image
CAMHI Sixteenth screen size high resolution

Default:

QUADLO

11.1 Image size

Target image size =

In the different screen modes of DVST each image is compressed to a target size and then transmitted.

SIZEFHI=Set target size (K):FULL HI RES
SIZEFLO=FULL LO RES
SIZEQHI=QUAD HI RES
SIZEQLO=QUAD LO RES
SIZEMULT=MULTISCREEN

DUALFHI=As above but for dual isdn operation
DUALFLO=
DUALQHI=
DUALQLO=
DUALMULT=

Target Picture Sizes :

SIZEFHI =20000(20000)
SIZEFLO =12000(12000)
SIZEQHI =8000(8000)
SIZEQLO =4500(4500)
SIZEMULT=2500(2500)
DUALFHI =20000(20000)
DUALFLO =14000(14000)
DUALQHI =8000(8000)
DUALQLO =4500(4500)
DUALMULT=2500(2500)

12 Alarms & Events

12.1 ALARM Settings

This section is included as reference for remote setup.

ASYS= *Set alarm system **ON** or **OFF**
(default, OFF)*

The alarm system is dormant until activated by the ASYS=ON command. When active the main display of the DVST will carry the message POLLING ALARM CONTACTS.

Note: Polling is the technical term used for checking if any alarm contacts are active.

When an alarm condition is detected the DVST transmitter dials stored number TEL0 from the dial menu. If a connection cannot be made to this number the unit dials stored number TEL1 from the dial menu. The transmitter will continue calling until a connection is made and the alarm is acknowledged from the receiver.

AON=n *Enable alarm contact n*
AOFF=n *Disable alarm contact n*
(default, all alarm contacts enabled)

By default all contacts are ON, or able to respond to contact closures on the alarm input.

Alarm inputs that are not used should be set to off.

Each input can respond to a contact closure or a contact opening, or respond to both.

ANOnn *Set contact nn normally open*

ANCnn *Set contact nn normally closed*

Images transmitted on alarm

The action taken on detection of an alarm is for the DVST unit to store a point of alarm image, dial the telephone number stored in dial menu number 0 and transmit the image.

The resolution of alarm images, and the screen mode in which they are transmitted can be selected with the following command:

ATYPEn= *HI* Selects a High resolution alarm image
 LO Selects a Low resolution alarm image

The alarm settings are displayed in the view mode as follows, (type VIEW <ENTER> and press a key until the following display appears)

Alarm	Number Alarm	Screen	Type	Contacts
01: ALARM 01	On	FULL	HI	N/O
02: ALARM 02	On	FULL	LO	N/O
03: ALARM 03	On	FULL	HI	N/C
04: ALARM 04	On	FULL	LO	N/C
05: ALARM 05	Off			
06: ALARM 06	Off			
07: ALARM 07	On	FULL	HI	N/O
08: ALARM 08	On	FULL	LO	N/O
09: ALARM 09	On	FULL	HI	N/O
10: ALARM 10	On	FULL	LO	N/O
11: ALARM 11	On	FULL	HI	N/O
12: ALARM 12	On	FULL	LO	N/O
13: ALARM 13	On	FULL	HI	N/O
14: ALARM 14	On	FULL	LO	N/O
15: ALARM 15	On	FULL	HI	N/O
16: ALARM 16	On	FULL	LO	N/O

When the alarm full command is set to on, any alarms occurring when the unit is on line will cause the respective camera to be displayed full screen.

AOUT= *Set alarm outputs **AUTO / MANUAL**
(default is **AUTO**)*

The two alarm contacts can be configured for automatic or manual operation.

AUTO

In automatic mode relay 1 acts as a line indicator and closes whenever the DVST is on line. Relay 2 closes only if an alarm has occurred and not yet been acknowledged.

MANUAL

In manual mode the AUX1 key on the local unit controls relay 1 on the remote unit, this works as a toggle on / off (latching) control. AUX2 on the local unit controls relay 2, which works as a momentary contact.

ALMODE= *...Set Alarm operation mode **OLNFRZ / FRZALL**
(default, **OLNFRZ**)*

OLNFRZ

Offline alarm freeze - Only freezes offline alarm images and then transmits these images to the receiver. Subsequent alarms incoming while the unit is transmitting to a receiver are flagged on the baseline but are not frozen, nor do they need to be acknowledged.

FRZALL

Freeze all alarm images - All alarm images are frozen. All must be acknowledged by the receiving station before the alarm can be cleared.

ADIAL=n *Set number of telephone entries to use in alarm
condition*

By default DVST transmitter dials stored number **TEL0**, if a connection cannot be made to this number the unit dials stored number **TEL1** on the menu. With **ADIAL=3** the DVST transmitter dials the stored numbers **TEL0**, **TEL1**, **TEL2** until a line answers

13 Audio

The Digital Audio Interface (DAL100) is a sound unit for the DVST range of products working on an intercom basis i.e. push-to-talk. Microphone and speaker connections are provided together with volume control and indicators for power, transmit, receive and line error.




Fig: 11 End Panel Layouts

13.1 Equipment required but not supplied

The following lists equipment you will need to complete your installation of the DAL100 audio unit.

- Microphone with automatic gain control and complete with push-to-talk switch and 3.5mm jack connector.
- Speaker capable of handling a 2W into 8 Ohm input.

13.2 Connecting the DAL100

Microphone (refer to fig. 11)

Connect the 3.5mm jack plug of the microphone into socket on end panel. Connect the microphone press-to-talk lead to pins 1 and 9 of a 15way male connector and plug into socket on end panel,




Fig: 12 Microphone connection

Speaker (refer to fig. 11)

Connect the 3.5mm jack plug of the speaker to the SPEAKER OUT socket.

Power Supply (refer to fig.11)

Connect the power supply to the socket marked PWR on the end panel.

DVST Connection (refer to fig.11)

Using the 9 way to 9 way cable connect the DAL100 unit to the AUX port on the DVST. (Details are in the cable section of this manual).

14 Cable Assemblies

The following pages detail cable assemblies with connectors for use with DVST transceivers which are available from Dedicated Micros. The cables are fully screened for EMC compatibility.

For prices and availability please contact our Sales Departments at the addresses below.

Northern UK Sales

Dedicated Micros Ltd
Pendlebury Industrial Estate, Bridge St, Manchester, M27 1FJ,
United Kingdom
Tel: 0161-727-3200 Fax: 0161-728-4142
Outside UK : Int +(44) 161-727-3200 Fax: Int +(44) 161-728-4142

Southern UK Sales

Dedicated Micros Ltd
3 Cannon Court, Warren Farm, Stratford Road,
Wolverton Mill, Milton Keynes MK12 5NS
Tel: 0908-225199 Fax: 0908-225197

In the United States

Dedicated Micros Inc.
11515 Sunset Hills Road, Reston, Virginia 22090, U.S.A.
Tel: Int +(1) 703-904-7738 Fax: Int +(1) 703-904-7743

In Australasia & the Far East


Dedicated Micros (Asia) PTE Ltd
1, Tannery Road, #05-04/05 Cencon I, Singapore 1334
Tel: +(65)-741-0138 Fax: +(65)-741-0221

Dedicated Micros (Australia) PTY
11 Leonard Street, Waitara, Sydney, NSW 2077, Australia
Tel: Int +(61) 2-482-1857 Fax: Int +(61) 2-482-1657

In France, Germany & Benelux

Dedicated Micros Ltd
Interleuvenlaan 64, B-3001 Leuven, Belgium
Tel: Int +(32)-16-40-1228 Fax: Int +(32)-16-40-0243

14.1 X21 to V35 Cable Assembly




9 WAY Female	V35 Male	Signal Name	CCIT Number
1			
2 ← Purple →	P	SD-A	103
3 ← Red →	H	DTR	108.2
4 ← Orange →	R	RD-A	104
5 ← Brown →	F	CO	109
6 ← Green →	V	SCR-A	115
7 ← →	AA	SCT-B	114
8 ← Black →	B	Gnd	102
9 ← Grey →	S	SD-B	103
10			
11 ← Yellow →	T	RD-B	104
12			
13 ← Blue →	X	SCR-B	115
14 ← White →	Y	SCR-A	114
15			

KEY

SC = Clock
 T = Transmit
 R = Recieve
 SD = Transmit Data
 RD = Recieve Data
 A/B = Signal Pairs


14.2 X21 Cable Assembly

X21 cable assembly



n/c = No Connection

14.3 V24 Async Cable Assembly




25 WAY
Male

25 WAY
Female

1 ←————→ 1
to All connections to
Pin to Pin to
25 ←————→ 25

14.4 V24 Sync Cable Assembly




25 WAY
Male

25 WAY
Female


1 ←————→ 1
to All connections to
Pin to Pin
25 ←————→ 25

14.5 RS232 Cable Assembly (DVST-PC)



n/c = No Connection

14.6 RS232 Cable Assembly (DVST-DAL)



15

Glossary

DVST	Digital Video Storage and Transmission
ISDN	Integrated Services Digital Network - A digital telephone system capable of transmitting data, speech, images and text.
PSTN	Public Subscriber Trunk Network - The standard telephone system used for speech and fax communication.
Speed of Update	The time taken to refresh a single picture.
Software Compression	Video data compression achieved by computer program processing.
Hardware Compression	Video data compression taking place in specialised purpose built microchips.
k bytes	Measurement expressing the size of digital computer memory
k bits per second	Measurement expressing the speed at which data can be transmitted.
Compression	Taking standard video signals and reducing these into compact digital data.
Decompression	Taking digitally compressed DVST information and restoring this to normal video images.
Complete compression	Each time the picture is transmitted, or stored to memory, the entire picture is compressed.
Conditional Updating	Update only the parts of the picture that have changed. The first time the picture is transmitted the entire picture is compressed. Thereafter only the parts of the picture that change are transmitted.
Teleconferencing	Providing a live, two way, sound & video link between two conference / meeting points.
DAT	Digital Audio Tape, the new technology for recording digital information on a special tape cassette. Massive storage can be achieved in a very small package.
MODEM	MOdulator/DEModulator used to connect the DVST unit to a standard telephone line.
Terminal Adapter	Used to connect the DVST to an ISDN digital telephone line.

16

Returns Procedure

In the Event of Difficulty

In the event of a fault, first approach your dealer or distributor. Dedicated Micros operates a Technical Support Group where most technical problems can be solved over the telephone. The addresses of Dedicated Micros are listed on the front page of this manual.

If, for what ever reason, this is not possible, the unit can be returned directly to a Dedicated Micros Repairs Department. In this event please follow the returns procedure as detailed below to avoid delay.

Photocopy the EQUIPMENT RETURN ADVICE. Contact the Customer Services Department to obtain a returns number.

The following information must be available to give to the Customer Services Department when requesting a returns number.

- Model type
- Serial number
- Full Account/Invoice address or Return Address if different
- Contact name
- Fax number and Telephone number
- Customer order number - for repair cost not exceeding £100
- Full description of the fault
- Previous returns number(s) (if applicable)

If the unit is rack mounted, the rack mount kit must be removed before the unit is packed. Wrap the unit in the original polythene bag. Fit preformed end pieces at either side of the unit.

If the unit is not returned in it's original packing, Dedicated Micros Repair Department will automatically re-box the unit, and there will be a charge of £11.75 inc VAT.

Mark the return number, obtained from the Customer Services Department, clearly on the outside of the box. Return the unit to the address on the front page of this manual, a completed copy of the EQUIPMENT RETURN ADVICE must be sent with the unit.

If the unit crosses a national boarder, enter Airway Bill number on the copy of the EQUIPMENT RETURN ADVICE and fax Dedicated Micros for the attention of the Despatch Department. This will avoid any delays in returning the unit after it has been repaired.

Notes:

Dedicated Micros tries to maintain a fast turnaround procedure for repairing equipment, incomplete or inaccurate documentation may result in delay.

If the unit is not under warranty a charge will be made for the repair.

If the unit has its warranty void, due to misuse or damage, the Repairs Department will contact the account customer to advise cost.

Upon examination of the unit if the repair cost is likely to exceed £100, the Repairs Department will contact the account customer for authorisation before work is undertaken.

Repairs not exceeding £100 will automatically be carried out and invoiced on the official order number stated by the account customer on the EQUIPMENT RETURN ADVICE.

EQUIPMENT RETURN ADVICE

Company Name:

Contact Name:

Invoice Address:

Tel. No.:

Fax No.:

Model/Type of
Equipment Returned:

Serial No.:

Returns Number:

Official Order Number:

Master Airway Bill Number:

Previous Returns Number: (if applicable)

Details of Reported Fault:

Returns Address for Unit:

DEDICATED MICROS

WORLDWIDE

Dedicated Microcomputer Group Ltd, *
16 Hilton Square, Swinton,
Manchester. M27 4FL
Telephone: 0161 727 3200
Fax: 0161 727 3300

Dedicated Micros Ltd,
Amberley, 33 - 35 Wellfield Road, Hatfield,
Hertfordshire, AL10 0BY
Telephone: 01707 373 013
Fax: 01707 259 898

Dedicated Micros Ltd, *
Interleuvenlaan 64,
B-3001 Leuven, Belgium
Telephone: +(32) 1640 1228
Fax: +(32) 1640 0243

Dedicated Micros USA, *
11515, Sunset Hills Road,
Reston, VA 22090.
USA.
Telephone: +(703) 904 7738
Fax: +(703) 904 7743

Dedicated Micros, Australia PTY,
Unit 1,
30, Leighton Place,
Hornsby, NSW 2077.
Australia.
Telephone: +(612) 9482 1857
Fax: +(612) 9482 1647

Dedicated Micros Asia PTE,
1, Tannery Road,
#05-04/05 Cencon 1,
Singapore 347719
Telephone: +(65) 741 0138
Fax: +(65) 741 0221

Dedicated Micros, (Malta) Ltd, *
UB2 San Gwann Industrial Estate,
San Gwann, SGN 09
Malta
Telephone: +(356) 483 673/4
Fax: +(356) 449 170

*

DOCUMENT PIN NUMBER MI-DMDF20/U3-0



BSIA
THE BRITISH SECURITY
INDUSTRY ASSOCIATION